Transceiver 2

Universal Insert Station

- Insert your unbalanced gear such as guitar pedals and old echo fx into your DAW or console via the Transceiver 2.
- Active DI-box with up to +20dB of gain. Plug your favorite instrument into your collection of vintage gear via the Transceiver 2.
- A re-amping tool.
- A Swiss Army Knife on stage. Connect balanced gear on stage between your instrument and amp.
- Blend function for the inserts.

Overview

The Transceiver is a four channel insert station. The main function is to convert balanced signals into unbalanced and back again without losing any signal quality. Each channel has a send level, a return gain control, a return polarity switch and a blend control. With the new added blend function you can choose how much of the inserted effect you want to add. The Transceiver 2 is a transformerless balanced design for the best possible signal handling, a flat frequency response and low harmonic distortion and noise. The balanced output has a high driving capability to drive input transformers, also the unbalanced send has a high driving capability.

Specification

Max balanced input: +27dBu

Max unbalanced send level: +21dBu

Max return input level: +21dB

Return gain: 0-20dB

Return input impedance: 1Mohm

Max balanced output: +27dBu

Features:

Send: TRS jack

Send level: 0 to full in 41 steps

Return: TRS jack

Return gain: 0 - 20dB in 41 steps

Polarity: flips the polarity of the return signal

Blend control from dry to wet in 41 steps

Regulated, internal power supply with a toroidal transformer

Selectable between 115 and 230V

Power consumption: 12VA

Specifications and components may be changed or updated without further notice.